



### Properties

|                   |                |
|-------------------|----------------|
| Base Construction | Steel          |
| Lens              | Acrylic        |
| Application       | Sconce         |
| Location          | Damp           |
| CRI               | 80             |
| Life Hours        | 50,000         |
| Light Source      | Integrated LED |

### Standard Selection

|         |                    |
|---------|--------------------|
| Voltage | 120V (non dimming) |
| Finish  | Black              |
| CCT     | 2700K              |

### Finish Options

- Black
- Bronze
- Brushed Nickel
- Gold/Brass
- White

### CCT Options

|     |                               |
|-----|-------------------------------|
| CCT | 2700K/3000K/3500k/4000K/5000K |
|-----|-------------------------------|

### Options

| Size   | Dimensions         | Wattage  | Voltage   | Lumens         |
|--------|--------------------|----------|---|----------------|
| BCF-12 | H:12" W:7"<br>E:3" | 10/15    | ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming) | 1300/1950      |
| BCF-15 | H:15" W:7"<br>E:3" | 15/20/25 | ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming) | 1950/2600/3250 |
| BCF-18 | H:18" W:7"<br>E:3" | 20/25/30 | ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming) | 2600/3250/3900 |
| BCF-24 | H:24" W:7"<br>E:3" | 20/25/30 | ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming) | 2600/3250/3900 |
| BCF-30 | H:30" W:8"<br>E:4" | 20/25/30 | ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming) | 2600/3250/3900 |
| BCF-42 | H:42" W:9"<br>E:3" | 30/35/40 | ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming) | 3900/4550/5200 |

## Options

BBX-Backbox W

¾" Conduit hole

EMG – Emergency

OS - Occupancy Sensor

OSCD - Occupancy Sensor Step Dimming

PC - Photo Control

**Not seeing what you're looking for?**

Contact us!

[info@asllighting.com](mailto:info@asllighting.com)