



Properties

Base Construction	Steel
Lens	Acrylic
Application	Flush Mount
Location	Damp
CRI	80
Life Hours	50,000
Light Source	Integrated LED

Standard Selection

Voltage	120V Triac dimming
Finish	Brushed Nickel
CCT	5CCT - 2700K / 3000K / 3500K / 4000K / 5000K

Finish Options

- | | |
|---|-------------------------------------|
| ☐ Black | ☐ Gold/Brass |
| ☐ Bronze | ☐ ORB |
| ☐ Brushed Nickel | ☐ White |

CCT Options

CCT 2700K/3000K/3500k/4000K/5000K/5CCT - 2700K / 3000K / 3500K / 4000K

Options

Size	Dimensions	Wattage	Voltage	Lumens
HDT-10	D:10" H:2.3"	10/15/20	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	1300/1950/2600
HDT-12	D:12" H:2.3"	10/15/20/25	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	1300/1950/2600/3250
HDT-14	D:14" H:2.3"	15/20/25	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	1950/2600/3250
HDT-16	D:16" H:2.3"	15/25/30	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	1950/3250/3900
HDT-18	D:18" H:2.3"	20/25/30	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	2600/3250/3900
HDT-20	D:20" H:5"	20/30/40	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	2600/3900/5200
HDT-24	D:24" H:5"	25/30/40	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	3250/3900/5200
HDT-28	L:28.3" W:14" H:4.4"	35	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	4550

Size	Dimensions	Wattage	Voltage	Lumens
HDT-32	L:32.3" W:18" H:4.4"	46	ND (120V (non dimming)) / TD (120V Triac dimming) / DV (120V-277V (non dimming)) / DVD (120V-277V 0-10 dimming)	5980

Options

- BBX-Backbox W
- ¾" Conduit hole
- OS - Occupancy Sensor
- OSCD - Occupancy Sensor Step Dimming

Not seeing what you're looking for?

Contact us!
info@asllighting.com